



## > Specification sheet

## Our energy working for you.™

## Description

The X3.3 has all the strength and reliability the genset industry has come to expect from the X Series range but in a smaller, lighter and more economical package. The X3.3 features direct fuel injection, resulting in cleaner, quieter and more fuel efficient performance. With a highly compact 4 cylinder envelope and extremely low heat rejection, the engine offers a high degree of installation flexibility.



This engine has been built to comply with CE certification.



This engine has been designed in facilities certified to ISO9001 and manufactured in facilities certified to ISO9001 or ISO9002.



## **Features**

Bosch direct injection in-line pump for cleaner, more efficient fuel consumption.

**Parent bore block** with deep, stiff crankcase and optimised rib arrangement to enhance strength and reduce noise.

**12 volt electrics package** as standard, with starter, alternator and fuel solenoid.

Minimal derate for high altitude or high ambient applications.

Shallow oil pan and single spin-on oil and fuel filter.

SAE '3/11.5' flywheel/flywheel housing.

Integrated Design - Coolpac products are supplied fitted with cooling package and heavy duty air cleaner for a complete power package. Each component has been has been specifically developed and rigorously tested for G-Drive products, ensuring high performance, durability and reliability.

**Service and Support** - G-Drive products are backed by an uncompromising level of technical support and after sales service, delivered through a world class service network.

## 1800 rpm (60 Hz Ratings)

Gross Engine Output			Net Engine Output			Typical Generator Set Output					
Standby	Prime	Base	Standby	Prime	Base	Standby	(ESP)	Prime	e (PRP)	Base	(COP)
kWm/BHP			kWm/BHP		kWe	kVA	kWe	kVA	kWe	kVA	
40/54	34/46	N/A	39/52	33/44	N/A	35	44	32	40	N/A	N/A



# **General Engine Data**

Туре	3 cycle, in-line, naturally aspirated		
Bore mm	91.4 mm (3.59 in.)		
Stroke mm	127 mm (5 in.)		
Displacement Litre	3.3 litre (199 in. <sup>3</sup> )		
Cylinder Block	Cast iron, 4 cylinder		
Battery Charging Alternator	37 amps		
Starting Voltage	12 volt, negative ground		
Fuel System	Direct injection		
Fuel Filter	Spin on fuel filters with water drain facility		
Lube Oil Filter Type(s)	Spin on full flow filter		
Lube Oil Capacity (I)	6.5		
Flywheel Dimensions	3/11.5		

# **Coolpac Performance Data**

Cooling System Design	Jacket water		
Coolant Ratio	50% ethylene glycol; 50% water		
Coolant Capacity (I)	8.6		
Limiting Ambient Temp.**	50		
Fan Power	1		
Cooling System Air Flow (m <sup>3</sup> /s)**	1.7		
Air Cleaner Type	Dry replaceable element with restriction indicator		
** @ 13 mm H <sup>2</sup> 0			

@ 13 mm H<sup>+</sup>0

# **Ratings Definitions**

## **Emergency Standby Power (ESP):**

Applicable for supplying power to varying electrical load for the duration of power interruption of a reliable utility source. Emergency Standby Power (ESP) is in accordance with ISO 8528. Fuel Stop power in accordance with ISO 3046, AS 2789, DIN 6271 and BS 5514.

#### Limited-Time Running Power (LTP):

Applicable for supplying power to a constant electrical load for limited hours. Limited-Time Running Power (LTP) is in accordance with ISO 8528.

### Prime Power (PRP):

Applicable for supplying power to varying electrical load for unlimited hours. Prime Power (PRP) is in accordance with ISO 8528. Ten percent overload capability is available in accordance with ISO 3046, AS 2789, DIN 6271 and BS 5514.

### Base Load (Continuous) Power (COP):


Applicable for supplying power continuously to a constant electrical load for unlimited hours. Continuous Power (COP) in accordance with ISO 8528, ISO 3046, AS 2789, DIN6271 and BS 5514.

# Weight & Dimensions

Length	Width	Height	Weight (dry)
mm	mm	mm	kg
1124	686	850	322

## Fuel Consumption 1800 (60 Hz)

%	kWm	BHP	L/ph	US gal/ph		
Standby Po	Standby Power					
100	40	54	11.3	2.9		
Prime Power						
100	34	54	9.1	2.4		
75	34	46	6.9	1.8		
50	17	23	4.8	1.2		
25	9	11	3.3	0.9		
Continuous Power						
100			TBD	TBD		



#### **Cummins G-Drive Engines**

#### Asia Pacific

10 Toh Guan Road #07-01 TT International Tradepark Singapore 608838 Phone 65 6417 2388 Fax 65 6417 2399

Europe, CIS, Middle East and Africa Manston Park Columbus Ave Manston Ramsgate Kent CT12 5BF. UK Phone 44 1843 255000 Fax 44 1843 255902

Rua Jati, 310, Cumbica Guarulhos, SP 07180-900 Brazil Phone 55 11 2186 4552 Fax 55 11 2186 4729

Latin America

Mexico Cummins S. de R.L. de C.V. Eje 122 No. 200 Zona Industrial

San Luis Potosí, S.L.P. 78090 Mexico Phone 52 444 870 6700 Fax 52 444 870 6811

#### North America

1400 73rd Avenue N.E. Minneapolis, MN 55432 USA

Phone 1 763 574 5000 USA Toll-free 1 877 769 7669 Fax 1 763 574 5298

#### Our energy working for you.™

www.cumminsgdrive.com

